




Control Your Video

**VIDEO WALLS VIDEO PROCESSORS
VIDEO MATRIX SWITCHES
EXTENDERS SPLITTERS WIRELESS
CABLES & ACCESSORIES**

32 x 32 HDBaseT Modular CAT5/6/7 Matrix with Bi-Directional IR/POE/Ethernet Control & Local Out



Model #: MSW-HBT4K-C6-32X32E

© 2015 Avenview Inc. All rights reserved.

The contents of this document are provided in connection with Avenview Inc. ("Avenview") products. Avenview makes no representations or warranties with respect to the accuracy or completeness of the contents of this publication and reserves the right to make changes to specifications and product descriptions at any time without notice. No license, whether express, implied, or otherwise, to any intellectual property rights is granted by this publication. Except as set forth in Avenview Standard Terms and Conditions of Sale, Avenview assumes no liability whatsoever, and claims any express or implied warranty, relating to its products are strictly prohibited.

Product Application & Market Sectors



Corporate



House Of Worship



Military



Residential



Education



Industrial



Medical



Aviation



TABLE OF CONTENTS

1.	GETTING STARTED	1
1.1	IMPORTANT SAFEGUARDS.....	1
1.2	SAFETY INSTRUCTIONS	1
1.3	REGULATORY NOTICES FEDERAL COMMUNICATIONS COMMISSION (FCC)	2
2.	INTRODUCTION	3
2.1	PACKAGE CONTENTS	4
2.2	OPERATION CONTROLS AND FUNCTIONS	5
2.2.1	Front Panel.....	5
2.2.3	Rear Panel	6
2.4	RS-232 PROTOCOLS.....	7
3.	APPLICATION DIAGRAM.....	8
4.	SPECIFICATIONS	9
	SW-HBT-HDM8IN-MOD 8 ports HDMI input module.....	10
	SW-HBT-DVI8IN-MOD 8 ports DVI input module	10
	SW-HBT-VGA8IN-MO 8 ports VGA Input module 8 ports DVI input module.....	11
	SW-HBT-DVI8OUT-MOD 8 ports DVI output module.....	11
	SW-HBT8O3P-MOD 8 ports HDBaseT output module	12
	SW-HBT8O4P-MOD 8 ports HDBaseT output module	12
5.	GENERAL TROUBLESHOOTING	13
6.	CAT5E/6/7 CABLE SPECIFICATION	14



SECTION I: GETTING STARTED

I.1 IMPORTANT SAFEGUARDS

Please read all of these instructions carefully before you use the device. Save this manual for future reference.

What the warranty does not cover

- Any product, on which the serial number has been defaced, modified or removed.
- Damage, deterioration or malfunction resulting from:
- Accident, misuse, neglect, fire, water, lightning, or other acts of nature, unauthorized product modification, or failure to follow instructions supplied with the product.
- Repair or attempted repair by anyone not authorized by us.
- Any damage of the product due to shipment.
- Removal or installation of the product.
- Causes external to the product, such as electric power fluctuation or failure.
- Use of supplies or parts not meeting our specifications.
- Normal wear and tear.
- Any other causes which does not relate to a product defect.
- Removal, installation, and set-up service charges.

I.2 SAFETY INSTRUCTIONS

MSW-HBT4K-C6-32X32E HDBaseT Modular Matrix Switcher has been tested for conformance to safety regulations and requirements, and has been certified for international use. However, like all electronic equipments, the MSW-HBT4K-C6-32X32E should be used with care. Read the following safety instructions to protect yourself from possible injury and to minimize the risk of damage to the unit.




- ⚠ Do not dismantle the housing or modify the module.
- ⚠ Dismantling the housing or modifying the module may result in electrical shock or burn.
- ⚠ Refer all servicing to qualified service personnel.
- ⚠ Do not attempt to service this product yourself as opening or removing housing may expose you to dangerous voltage or other hazards
- ⚠ Keep the module away from liquids.
- ⚠ Spillage into the housing may result in fire, electrical shock, or equipment damage. If an object or liquid falls or spills on to the housing, unplug the module immediately.
- ⚠ Have the module checked by a qualified service engineer before using it again.
- ⚠ Do not use liquid or aerosol cleaners to clean this unit. Always unplug the power to the device before cleaning.



1.3 REGULATORY NOTICES FEDERAL COMMUNICATIONS COMMISSION (FCC)

This equipment has been tested and found to comply with Part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.

Any changes or modifications made to this equipment may void the user's authority to operate this equipment.

Warning symbols	Description
	<p>ONLY USE THE PROVIDED POWER CABLE OR POWER ADAPTER SUPPLIED. DO NOT TAMPER WITH THE ELECTRICAL PARTS. THIS MAY RESULT IN ELECTRICAL SHOCK OR BURN.</p>
	<p>DO NOT TAMPER WITH THE UNIT. DOING SO WILL VOID THE WARRANTY AND CONTINUED USE OF THE PRODUCT.</p>
	<p>THE VIDEO BOARDS ARE VERY SENSITIVE TO STATIC. PLEASE ENSURE IF RACK MOUNTED OR INSTALLED ON A SURFACE, IT SHOULD BE IN A GROUNDED ENVIROMENT.</p>

	<p>⚠ WARNING</p> <p>Read & understand user guide before using this device.</p> <p>Failure to follow the proper installation instructions could result in damage to the product and preventing expected results.</p>
---	--

2. INTRODUCTION

The Modularized Matrix series are designed to route the signal of 32 sources to any connected 32 displays, providing resolutions of Ultra HD 1080p (1920 x 1080) / 4Kx2K (3840 x 2160) and WUXGA (1920x1200@60HzRB). Besides the regular matrix functionality, the matrix models are very attractive to the integrators because of their great flexibility, with the most advanced modularization design these models can be setup as a matrix of HDMI, DVI-D, CAT5e/6/7, VGA or their any combinations (count with eight, for example, a matrix with 8-HDMI-in/8-DVI-IN and 8-HDMI-OUT/8-DVIOUT),all you need to do is to swap the input or output modules as you wish. Refers to section 8 for available module boards..

- HDMI, HDCP 1.1 and DVI 1.0 compliant;
- Interchangeable input and output boards;
- Input and output module types can be mixed and added in increment of 8 from 8x8 up to 32x32 with HDMI, DVI, CAT5e/6/7 and VGA interfaces;
- Supports LPCM 7.1CH, Dolby TrueHD, Dolby Digital Plus and DTS-HD Master Audio transmission;
- Supports a wide range of PC and HDTV resolutions from VGA to WUXGA and 480i to 1080p or 4Kx2K;
- Supports RS-232, Telnet and Web GUI controls;
- Supports redundant power supply;
- HDMI cable length with a resolution 1080p/8bits&12bits the Input/ Output source can be 15m/15m(8bits) and 10/10m(12bits) away;
- CAT5e/6/7 cable length with a resolution 1080p/8bits&12bits the Input/Output source can be 100m/100m away;
- EDID modes:
 - a. Standard mode: Factory Default
 - b. Automatic mode: Taking EDID from the lowest output port
 - c. Manual mode: Can assign any output to any input port
- HDBaseT 5Play™ convergence: Video, Audio, PoE, Ethernet & Control (IR & RS-232).




2.1 PACKAGE CONTENTS

1	ENCLOSURE OF MODULARIZED 32X32 MATRIX (INCLUDING CONTROL BOARD & POWER)	
2	INPUT MODULE BOARD OF HDMI/DVI/CAT5E/6/7 OR VGA(OPTIONAL)	
	OUTPUT MODULE BOARD OF HDMI/DVI/CAT5E/6/7 (OPTIONAL)	
	POWER CORD	
	USER'S MANUAL	



2.2 OPERATION CONTROLS AND FUNCTIONS

2.2.1 FRONT PANEL



1. POWER button & LED: Power On device with first press or second press to activate standby mode		
2. LCM: Displays the user selected settings and to allow unit setup functions when Menu is pressed. Display also Input / Output info		
3. LOCK button & LED: Press this button to lock all the function buttons on panel. The LED will illuminate, to unlock press it again.		
4. RETURN: Press this button to return back/exit the current selection.		
5. MENU: Press this button to enter into the menu selections of A. EDID	A. EDID	
	1. Auto EDID: Base on the first connected output TV/Display's EDID from 1~16 ports.	2. Standard EDID: Use the built-in EDID which supports video up to 1080p@60/WUX-GA@60RB and audio supports LPCM 2CH.
	3. Manual EDID: Support independent EDID by appoint input and output ports.	
	B. IP	
1. IP address,	2. Netmask,	3. Gateway.



C. Temperature	
1. Temperature 1,	2. Temperature 2,
these figures shows the temperature of the device inside.	
D. LCM Contrast Range from 1~4	

6. PAGE : This button allows the user to navigate through the different page info displayed.
7. SAVE: Saves the preset settings of the I/O. 3 Preset save spaces available.
8. RECALL: Press this button to recall from the saving settings of 1~3.
9. ENTER: To Confirm or Enter the selection
10. ALL: select all outputs source.
11. OUT/IN: Select input source to displaying on output display. The sequence should be OUT/IN → number(s) for output source → OUT/IN → a number for input display → Enter.
12. 0~9: Press these numbers when selecting input output ports.
13. +: When selecting more than one output for an input selection. This button works correspondingly with OUT/IN button only.

2.2.3 Rear Panel



1. OUTPUT 1~16: Connect to HD or 3D screens /monitors with HDMI cables up to 16 displays.	
2. CPU	A. RS-232: Connect with D-Sub 9-pin cable from the PC/Laptop device for RS-232 control over the Matrix or the connected device(s).
	B. CONTROL: Connect to an active network line for LAN serving and Telnet/Web GUI control.
	C. IR OUT/IN: Reserved.
	D. SERVICE: This port is reserved for firmware update only.
	E. OUTPUT 0: Connect to DVI/HDMI (with DVI to HDMI adaptor) screen/monitor for local output monitoring
3. INPUT 1~16: Connect to source equipment such Blu-ray/Set Top Box players up to 16 sets with HDMI cables.	
4. POWER & POWER Supply: The device will automatically turns ON when power is supplied.	
5. Ventilation Fan: This fan will automatically turns ON when the device is switch to ON. Do not block this port of the device or cover it with any object. Please allow adequate space around the unit for air circulation.	



2.4 RS-232 PROTOCOLS

SW-HBT-C6POE-16x16E	
PIN	Definition
1	NC
2	TxD
3	RxD
4	NC
5	GND
6	NC
7	NC
8	NC
9	NC

Third Party RS-232 Controller	
PIN	Definition
1	NC
2	RxD
3	TxD
4	NC
5	GND
6	NC
7	NC
8	NC
9	NC

Baud Rate: 19200bps

Data Bit: 8 bits

Parity: None

Stop Bit: 1

Flow Control: None




3. APPLICATION DIAGRAM

MSW-HBT4K-C6-32x32E

1080p(1920x1080) = 100m (330 feet) CAT6E 250MHz
 4K(3840x2160) = 70m (230 feet) CAT6E 250MHz

CABLE INDEX

- Input / Output ■
- RS-232 ■
- IR ■
- CAT-5e / CAT-6 ■
- LAN NETWORK ■



4.

SPECIFICATIONS

ITEM	DESCRIPTION
UNITS	SW-HBT4K-C6-32X32E
UNIT DESCRIPTION	4K HDBaseT ModlarHDMI Matrix Switcher with IR/RS232/POE/4k2k support
HDCP	YES
LAN / ETHERNET	100Mbps
VIDEO BANDWIDTH	300 MHz (10.2Gbps)
SUPPORTED RESOLUTIONS (Based on Card Module Installed)	480i~1080p@50/60, 1080p@24, 3D 4K@30 Up to Ultra HD (3840x2160@24/25/30Hz) 4K2K-(4096x2160@24Hz)
AUDIO SUPPORT	LPCM 7.1CH, Dolby TrueHD, Dolby Digital Plus and DTS-HD Master Audio
HDMI IN CABLE M/M	15m/1080p@8-bit or 6m/1080p@12-bit
ESD PROTECTION	Human body model — ±8kV (air-gap discharge) & ±4kV (contact discharge)
INPUT	32 x HDMI or DVI or CAT5e/6/7 or VGA
OUTPUT	32 x HDMI or DVI or CAT5e/6/7
RS 232	Supported
HDMI CONNECTOR	Type A (19 pin female)
IR FREQUENCY	30~50kHz
DIMENSIONS (L X W X H)	19.5" x 19" x 9" 494 mm (L)×482 mm (W)×233mm (H)
NET WEIGHT	33 lbs
POWER SUPPLY	2 x AC 110~240V (US/EU standards, CE/FCC/UL certified)
POWER CONSUMPTION	230 W
ENVIRONMENTAL	
OPERATING TEMPERATURE	32° ~ 104°F (0° to 40°C)
STORAGE TEMPERATURE	-4° ~ 140°F (-20° ~ 60°C)
RELATIVE HUMIDITY	20~90% RH (non-condensing)





SW-HBT-HDM8IN-MOD 8 ports HDMI input module

Video Bandwidth	225MHz/6.75Gbps
Input ports	8 * HDMI
Video resolutions	PC: VGA ~WUXGA@60RB HD: 480i~1080p
Audio transmission	LPCM7.1CH, Dolby TrueHD, Dolby Digital Plus, DTS-HD Master Audio (32~192KHz Fs sample rate)



SW-HBT-DVI8IN-MOD 8 ports DVI input module

Video Bandwidth	225MHz/6.75Gbps
Input ports	8 * DVI
Video resolutions	PC: VGA ~WUXGA@60RB HD: 480i~1080p
Audio transmission	LPCM7.1CH, Dolby TrueHD, Dolby Digital Plus, LPCM7.1CH, Dolby TrueHD, Dolby Digital Plus, rate)





SW-HBT-VGA8IN-MO 8 ports VGA Input module 8 ports DVI input module

Input ports	8 * VGA, 8 * 2.5mm Audio phone jack
Video resolutions	PC: VGA ~WUXGA@60RB
Audio transmission	LPCM7.1CH, Dolby TrueHD, Dolby Digital Plus, DTS-HD Master Audio (32~192KHz Fs sample rate)



SW-HBT-DVI8OUT-MOD 8 ports DVI output module

Video Bandwidth	225MHz/6.75Gbps
Input ports	8 * DVI
Video resolutions	PC: VGA ~WUXGA@60RB HD: 480i~1080p
Audio transmission	LPCM7.1CH, Dolby TrueHD, Dolby Digital Plus, DTS-HD Master Audio (32~192KHz Fs sample rate)





SW-HBT803P-MOD 8 ports HDBaseT output module

Video Bandwidth	225MHz/6.25Gbps
Features	Support HDBaseT/IR/RS232
Output ports	8 * CAT5e/6, 8 * IR Extender, 8 * IR Blaster
Video resolutions	PC: VGA ~ WUXGA HD: 480i~1080p
IR Frequency	30~50Hz
Audio transmission	LPCM7.1CH, Dolby TrueHD, Dolby Digital Plus, DTS-HD Master Audio (32~192KHz Fs sample rate)



SW-HBT804P-MOD 8 ports HDBaseT output module

Video Bandwidth	300MHz/10.2Gbps
Features	Support HDBaseT/PoE/IR/RS232
Output ports	8 * CAT5e/6, 8 * IR Extender, 8 * IR Blaster
IR Frequency	30~50Hz
Video resolutions	PC: VGA ~ WUXGA HD: 480i~1080p
Audio transmission	LPCM7.1CH, Dolby TrueHD, Dolby Digital Plus, DTS-HD Master Audio (32~192KHz Fs sample rate)



5. GENERAL TROUBLESHOOTING

PROBLEM	SOLUTION
NO IMAGE	<ul style="list-style-type: none"> • Check if connection to the source and the display are correct. • Ensure that display device supports 480p, 720p and 1080p 4K@30 resolution • Terminated to 568B standard with Shielded Ends Recommended • High Quality CAT5/6/7 Cable helps signal transmission • Please use the supplied power supply-DC 24V/6.25A DC • Check LED Link light see (Section 3 Panel Description) • Check LED Sync light see (Section 3 Panel Description)
EDID ISSUE	<ul style="list-style-type: none"> • EDID MODE-TV: The default factory setting is on TV. The unit will detect the 1st CAT5e/6/7 output's EDID. When obtained a (4K2K) Ultra HD 3840x2160 EDID the signal is transmitted. • If the 1st CAT5e/6/7 output is without a Ultra HD 3840x2160 EDID the unit will detect all output's EDID and Transmit the signal that all outputs can accept. • EDID MODE-STD: Switch to STD to use built-in EDID if the display has No Image. STD EDID's video at 1080p@60Hz and audio at LPCM 2CH.
Set-Top Box No Picture	<ul style="list-style-type: none"> • HDBaseT and HDMI 1.3 standards support CLOCK STRETCHING for i2c buss protocol • Example set top boxes like Scientific Atlantic results no picture. This can be resolved by swapping out the box for a newer version that supports HDMI 1.3 not HDMI 1.2
NO Infrared Communication	<ul style="list-style-type: none"> • Ensure the UTP cable is run within the wall away from EMI and High Voltage power Lines. • Please check manual of device to ensure proper placement of IR Blaster on IR EYE. • Some LED /Plasma TV have EMI interference with the IR Extender, please place the IR Rx 3-6" away from Screen
Recommended TEST	
End-to-End Testing	HDBaseT system, a final end-to-end test of all the A/V components should take place. These tests include checking the HDMI stream at the far end (sink end), the clock rate, frame compare, video pattern, audio, EDID and HDCP with Quantum 780 (recommended)
Passive Monitoring:	Passive monitoring enables an integrator to view the HDCP transactions, EDID exchange, as well as the connection events between the actual devices in the network.

NOTE

Additional info on Guidelines to Test & Troubleshoot HDBaseT Systems Can be retrieved from our website under the category Downloads for this product SW-HBT4K-C6-32X32E



COUT-8CVL-3PLAY Cable Distance
SW-HBT8O3P-MOD 8 ports HDBaseT output module

Cable Type	Range	Pixel Clock Rate	Video Data Rate	Supported Video
CAT5e/6/7	60 m	<=225 MHz	<=5.3 Gbps (HD Video)	Up to 1080p, 60 Hz, 36 bits, 3D (data rates lower than 5.3 Gbps or below 225 MHz TMDS clock).
	40 m	>225 MHz	> 5.3 Gbps (Ultra HD Video)	4K2K, 30Hz video, formats

COUT-8CV-4PLAY & COUT-8CV-5PLAY Cable Distance
SW-HBT8O4P-MOD 8 ports HDBaseT output module

Cable Type	Range	Pixel Clock Rate	Video Data Rate	Supported Video
CAT5e/6/7	100 m	<=225 MHz	<=5.3 Gbps (HD Video)	Up to 1080p, 60 Hz, 36 bits, 3D (data rates lower than 5.3 Gbps or below 225 MHz TMDS clock).
	70 m	>225 MHz	> 5.3 Gbps (Ultra HD Video)	4K2K, 30Hz video, formats



Avenview Warranty Certificate

AVENVIEW CORP. ("Avenview") warrants Avenview-branded product(s) contained in the original packaging against defects in materials and workmanship when used normally in accordance with Avenview's enclosed manual guidelines for a period of THREE (3) YEARS from the date of original retail purchase - Warranty Period. Avenview's published guidelines include but are not limited to information contained in technical specifications, user manuals and service communications.

LABOR: During the Warranty Period of THREE (3) YEARS, Avenview will repair or replace the product(s) at no cost using new or used parts equivalent to novel performance and reliability if the product(s) is determined to have abide by Avenview's published guidelines. Cost of Labor applicable to product(s) after Warranty Period. For labor costs, please contact support@avenview.com.

PARTS: During the Warranty Period of THREE (3) YEARS, Avenview will supply new or rebuilt replacements in exchange for defective parts of the product(s) at no cost if the product(s) is determined to have abide by Avenview's published guidelines. Cost of Parts applicable to product(s) after Warranty Period. For part(s) costs, please contact support@avenview.com.

To obtain Warranty: (a) proof of purchase in the form of a bill of sale or receipted invoice reflecting that the registered product(s) is within warranty period must be presented to obtain warranty service; (b) product(s) must be registered at time of purchase. Failure to do so will result in applicable parts and labor charges. Returning product(s) must be shipped in Avenview's original packaging or in packaging pertaining equal degree of protection to Avenview's. Both Avenview and purchaser are responsible for freight charges and brokerages when shipping the product(s) to the receiver.

NOT COVERED BY THIS WARRANTY

This warranty does not apply to any non-Avenview branded product(s); non-registered Avenview product(s). This warranty does not apply: (a) to cosmetic damage, including but not limited to scratches, dents and broken cords; (b) to damage caused by use with another product; (c) to damage caused by accident, abuse, misuse, liquid contact, fire, earthquake or other external cause; (d) to damage caused by operating the Avenview product(s) outside Avenview's manuals or guidelines; (e) to damage caused by service performed by anyone who is not a representative of Avenview or an Avenview authorized personnel; (f) to defects caused by normal wear and tear or otherwise due to the normal aging of the Avenview product(s), or (g) if any serial number has been removed or defaced from the Avenview product(s).

AVENVIEW IS NOT LIABLE FOR DIRECT, SPECIAL, INCIDENTAL OR CONSEQUENTIAL DAMAGES RESULTING FROM ANY BREACH OF WARRANTY OR CONDITION, OR UNDER ANY OTHER LEGAL THEORY, INCLUDING BUT NOT LIMITED TO LOSS OF USE; LOSS OF REVENUE; LOSS OF ACTUAL OR ANTICIPATED PROFITS (INCLUDING LOSS OF PROFITS ON CONTRACTS); LOSS OF THE USE OF MONEY; LOSS OF ANTICIPATED SAVINGS; LOSS OF BUSINESS; LOSS OF OPPORTUNITY; LOSS OF GOODWILL; LOSS OF REPUTATION; LOSS OF, DAMAGE TO, COMPROMISE OR CORRUPTION OF DATA; OR ANY INDIRECT OR CONSEQUENTIAL LOSS OR DAMAGE REPAIR OR REPLACEMENT AS PROVIDED UNDER THIS WARRANTY IS THE EXCLUSIVE REMEDY OF THE CONSUMER.

Some states do not allow the inclusion or limitation of incidental or consequential damages, or allow limitations on duration implements of the Warranty Period; therefore the above limitations or exclusions may not be applicable to you. This warranty gives you specific legal rights, and you may have other rights which vary from state to state.



275 Woodward Avenue, Kenmore, NY 14217
1.866.508.0269





AV Connectivity, Distribution And Beyond...

TECHNICAL SUPPORT

CONTACT US



Phone: 1 (866) 508 0269



Email: support@avenview.com



USA Head Office Avenview Corp. 275 Woodward Avenue Kenmore, NY 14217

USA Head Office

Office Avenview
Corp. 275 Woodward Avenue
Kenmore, NY 14217
Phone: +1.716.218.4100 ext223
Fax: +1.866.387-8764
Email: info@avenview.com

Canada Sales

Avenview
151 Esna Park Drive, Unit 11 & 12
Markham, Ontario, L3R 3B1
Phone: 1.905.907.0525
Fax: 1.866.387.8764
Email: info@avenview.com

Avenview Europe

Avenview Europe
Demkaweg 11
3555 HW Utrecht
Netherlands
Phone: +31 (0)85 2100- 613
Email: info@avenview.eu

Avenview Hong Kong

Unit 8, 6/F, Kwai Cheong Centre,
50 Kwai Cheong Road,
Kwai Chung, N.T.
Hong Kong
Phone: 852-3575 9585
Email: wenxi@avenview.com

Disclaimer

While every precaution has been taken in the preparation of this document, Avenview Inc. assumes no liability with respect to the operation or use of Avenview hardware, software or other products and documentation described herein, for any act or omission of Avenview concerning such products or this documentation, for any interruption of service, loss or interruption of business, loss of anticipatory profits, or for punitive, incidental or consequential damages in connection with the furnishing, performance, or use of the Avenview hardware, software, or other products and documentation provided herein.

Avenview Inc. reserves the right to make changes without further notice to a product or system described herein to improve reliability, function or design. With respect to Avenview products which this document relates, Avenview disclaims all express or implied warranties regarding such products, including but not limited to, the implied warranties of merchantability, fitness for a particular purpose, and non-infringement.