





2. Go to Switching ---> Global Parameters ---> Enable IGMP Snooping Status



3. Go to Switching ---> Multicast Support ---> IGMP Snooping ---> set IGMP Snooping Statu to Enable, set IGMP Querier Status to enable




4. Go to Switching ---> Multicast Support ---> Unregistered Multicast ---> Summary and Select ALL ---> Press Apply



5. **SAVE** settings to the boot configuration. Unsaved changes will be lost when the switch is power cycled. Once the coniguration is saved, power down the switch and connect all the HDM-C6VWIP-SET Tx & Rx devices.

The **HDM-C6VWIP-SET** have to communicate at the group of **224.0.0.251**. This group should be added manually into Dell Switcher and place the corresponding ports to be static into the group.



The **Avenview CTRLPRO-VWIP**, IP Controller simply provides communication to our HDM-C6VWIP-SET and third party controllers to communicate, Telnet and RS-232 commands to automate high definition video and high quality audio to many screens. This device can be accessed from a WEB Browser and allow control commands to Avenview Video IP solution

